

DATA SHEET 2021





## **KEY FEATURES**

- Easy install
- Easy retrofit for existing camlocks
- Front battery change
- Key Override
- **Battery Override**
- Private and Public Functions
- Up to 20 User Codes
- Auto-unlock after a set time
- Slam latch accessory available
- Black Chrome / Silver Chrome finishes

# KL1000 G3

Introducing the new KitLock KL1000 G3 cabinet lock. Key override and front battery change capabilities provide ease of use and peace of mind. The updated chrome effect back panel and handle finishes reflect their surroundings giving the lock a slimmer, more subtle aesthetic.

Sharing the same fittings & fixings as the KL1000 Classic, this lock is easily retrofitted, ideal for upgrading existing installations with increased flexibility and convenience for both guests and staff.

### **KEY OVERRIDE**

Allows key holders to access the locker in the event of a forgotten code or an emergency. Override key available separately.

## FRONT BATTERY CHANGE

The KL1000 G3 battery compartment can be accessed via the front of the lock. Entering a valid code and turning the handle reveals a security screw which, once removed, allows the cover to slide up and batteries to be replaced.

# TECHNICAL SPECIFICATION

DESCRIPTION
8 digit Master and Sub-Master Code, 6 digit Technician Code, 4 digit User Code
Override key available separately
Up to 100,000 operations per 2 x AAA batteries
Red LED will flash on opening to indicate low battery
A 9 volt PP3 battery can be placed against external contacts
Vertical, right and left hand models
When used with gasket (available separately) IP55 available for special order
Flat and cranked cam supplied
Ready to fit doors up to 25mm (1")
Fitted with 24mm ( $^{15}/_{16}$ ") spindle as standard, optional 10mm ( $^{3}/_{8}$ ") and 29mm ( $^{11}/_{8}$ ") spindles supplied
136mm (5 <sup>3</sup> / <sub>8</sub> ") H x 28mm (1 <sup>1</sup> / <sub>16</sub> ") D x 33mm (1 <sup>5</sup> / <sub>16</sub> ") W
Retrofit to existing KL1000 G3 locks or purchase for new locks (available separately)

Note: Not suitable for poolside lockers.

## **FUNCTIONS**

## **Private Function**

This is used where the same code will be repeatedly used, e.g. an employee with a personal locker/drawer.

### **Public Function**

This is the default function and is already pre-programmed in new locks. In this function the KitLock operates with a single User Code. The user enters a personal four digit code, this locks the lock. The same code is entered once only to open the lock and is automatically erased. The lock remains open ready for the next user. This function is used for short term, multiple occupancy applications.